

Activating a Bongo DataLink with FirstNet

After the activation form has been submitted on Bongotechnologies.com and the confirmation of activation email has been received, you're ready to finish configuring the device using the below steps.

1. Inside the Simplifi Connect 2 box, there is a USB adaptor. Plug the USB adaptor into the router, and then run an ethernet cord into a network jack within your office. This will provide internet to the router to allow for configuration.



- 2. Navigate to: <u>https://portal.simplifi.io/routers</u>
 - a. Login to the remote management platform with your credentials. If you do not have credentials, please contact Brad @ Bongo (920) 371-9352
- 3. In the top left corner of the screen, search for the IMEI of the device you're working on.

4. Click on the IMEI once it is found and scroll down to "Advanced Information."

Total: 1 router(s)		
IMEI	Router Status	Model
<u>866834045820870</u>	⊲⊳ Disconnected	BS6425L-AF-11

5. Under Cellular WAN – Click the Pencil to edit the device.

Cellular WAN	× ±
Protocol	DHCP Client
IP Address	10.17.100.212
IMEI	866834045247504
Netmask	255.255.255.248
Gateway	10.17.100.213
DNS 1	107.112.201.135
DNS 2	-
DNS 3	-
Expires	1h 59m 27s
Connected	33s

6. Update the APN box to say: **firstnet-broadband**

and then press save.

APN	Authentication Type	
firstnet-broadband	Select	~
PIN	Allowed Modes	
	Automatic	~
PAP/CHAP username	IP Family	
	IPv4	`
PAP/CHAP password	Allowed Bands	
C	Select	
	Disable Roaming	
	Cancel	Save

- 7. Unplug the USB dongle from the device, and then power cycle the device.
- 8. Once the unit shows a solid green status light, you're ready to test the cellular connection and connect your devices.